



# Android Manual

USB Driver Manual






# Bluebird Android USB Driver installation



# USB Driver installation (1/6)

- Please connect the device with your PC -> Open Device Manager -> Android device with an exclamation mark will be appeared under Other device -> Click right mouse on the Android device -> Click Update Driver Software.




# USB Driver installation (2/6)

- Click Browse my computer for driver software -> Click Browser




# USB Driver installation (3/6)

- Please select Bluebird\_usb\_driver -> Click OK  
(Please use the sent "Bluebird\_usb\_driver")





# USB Driver installation (4/6)

- Please check the correct path where you downloaded in the device. -> Click Next




# USB Driver installation (5/6)

- When Windows Security window is appeared, please select “install this driver software anyway”



# USB Driver installation (6/6)

- If you can see the Bluebird ADB Interface under the Android Device, you installed USB Driver successfully.



# Download Image

## BOS Loader Description

Version

Select for Folder of  
Downloading  
Package

Model Selection

다운로드 정보

모델선택: EF501

Memory: 해당사항없음

H/W:

폴더 경로: D:\bb\_model\_image\EF501\Android70\EF401-EF501-AND71-EN-20180830\_R1.12-u:

Checksum: 유효성검증 완료

폴더 선택

파티션 정보

<input checked="" type="checkbox"/> modem	<input checked="" type="checkbox"/> sbl1	<input checked="" type="checkbox"/> sbl1bak	<input checked="" type="checkbox"/> rpm	<input checked="" type="checkbox"/> rpmbak	<input checked="" type="checkbox"/> tz	<input checked="" type="checkbox"/> tzbak	<input checked="" type="checkbox"/> devcfg
<input checked="" type="checkbox"/> devcfgbak	<input checked="" type="checkbox"/> dsp	<input checked="" type="checkbox"/> aboot	<input checked="" type="checkbox"/> abootbak	<input checked="" type="checkbox"/> boot	<input checked="" type="checkbox"/> recovery	<input checked="" type="checkbox"/> system	<input checked="" type="checkbox"/> cache
<input checked="" type="checkbox"/> lksecapp	<input checked="" type="checkbox"/> lksecappbak	<input checked="" type="checkbox"/> cmnlib	<input checked="" type="checkbox"/> cmnlibbak	<input checked="" type="checkbox"/> cmnlib64	<input checked="" type="checkbox"/> cmnlib64bak	<input checked="" type="checkbox"/> keymaster	<input checked="" type="checkbox"/> keymasterbak
<input checked="" type="checkbox"/> mdtp							

Device ID (EFXXXXXXXXX)

다운로드 대기중... 경과시간: 00:00

```
Microsoft Windows [Version 10.0.17134.228]
(c) 2018 Microsoft Corporation. All rights reserved.
C:\Program Files (x86)\Bluebird\Customer_Version>adb start-server
```

Flash Completed 0%

다운로드 시작

디바이스 찾기

Connected Device ID  
Information

Information for  
Downloading State



Start Button for  
Downloading

Search for Device  
Connecting through USB

# Download Image


## Download Process

1. Run the program > Select model > Select folder which image is located.




### 2. Select folder which image is located.

- Ready for downloading is shown when images for downloading are properly located.




### 3. Search for Device and Start with Downloading

- I. Fundamentally, the program automatically searches for a device connected through USB and gets it connected.
  - If it automatically does not get it connected, search for the device connected through USB through clicking **Searching for Devices** to get it connected manually.
- II. If the connected device exists, automatically, the **Download Start** button is activated so that click the **Download Start** button to start downloading the images.



### 4. Proceed Downloading

- I. The progress bar is incremented on BOS Loader application
- II. The device is automatically entered in **FASTBOOT mode**.




Desktop Side




PDA Side

### 5. Complete Downloading

- I. The device is automatically restarted when downloading is complete with the message, **Download is completed!!** and the progress bar for downloading reaches 100% with the message, **Flash Completed 100%**.
- II. The device is on Bluebird splash screen for approx. 3 - 5 minutes before Welcome screen is displayed.



Desktop Side






PDA Side





### ❌ Install Driver (Bluebird-USB-Drivers-V0.9.4.zip)

1. Unzip “Bluebird-USB-Drivers-V0.9.4.zip”
2. Connect EF501 to PC
  - I. If you already install drivers, you don't need to install driver when the device is connected to PC
3. Select “Android” in device manager
4. Update driver one by one
  - I.  Android Click on right mouse button on this icon
  - II. Update driver -> Browse my computer for driver software -> Select **Bluebird-USB-Drivers-V0.9.4** folder -> Next



### ✳ Install Driver (Bluebird-USB-Drivers-V0.9.4.zip)

3. If “Windows Security” pop-up window appears, check the check box “**Always trust BlueBird.inc S/W**” and click “**install**” button
4. Finish driver update and click “**close**” button



6. Update the rest of  the same way if it still exists
7. Do the download image step again



Thank you!