

HW Repair Guide SM-T310 (LT01)

Samsung GALAXY S III
designed for humans



inspired by nature

June, 2013

HHP Global CS team

SAMSUNG

1. All functionality, features, specifications and other product information provided in this document including, but not limited to, the benefits, design, pricing, components, performance, availability, and capabilities of the product are subject to change without notice or obligation. Samsung reserves the right to make changes to this document and the product described herein, at anytime, without obligation on Samsung to provide notification of such change.


2. In data of our company, important management / technical information is included, and if it is leaked, loss can happen in various aspect such as closing a technology gap, increasing ability to respond.

Therefore, it is strictly prohibited from information leak or forwarding this material, and if leak of management / technical information due to disobeying the law happens, it can be severely punished in accordance with information protection rule of our company.

1. Introduction of LT01
2. Service Guide
 - Boot Recovery
3. Repair Guide
 - Assembly & Disassembly
 - Electronic Components
 - SMD parts
 - Trouble Shooting
4. Q&A

- **Feature**

- 8" Display
- Slim Design Tablet



- **Specification**

Item	spec.
AP	1.5GHz Dual Core (Exynos 4212)
OS	Android JB Prime
Memory	16GB NAND + 1.5GB RAM
Display	8" TFT (1280x800)
Camera	5MP + 1.3MP
Sensor	Accelerometer, Magnetic, Light
Connectivity	BT4.0, WiFi a/b/g/n
GPS	A-GPS + GLONASS
Battery	4450mA

– Brief JTAG process for SM-T310


- 1) Copying Bootloader File to external SD Card, using normal SM-T310
- 2) inserting the SD card to defective phone, and copy the bootloader file to the defective Phone
- 3) After downloading bootloader file to the defective phone, enter the download mode with the phone, and download Full S/W(PIT, PDA, CSC)

– Pre-requisite


- 1) One normal SM-T310(normally booted on)
- 2) External SD Card (memory size should be bigger than 2GB)
- 3) Odin3 v3.07.exe and Odin3.ini
- 4) SM-T310_Boot_Recovery.tar (uploaded on HHPsvc > Find Contents > J-TAG Program > SM-T310)

- Detailed JTAG Process


- 1) Insert External SD Card to normal phone to copy Bootloader to SD card.
- 2) Run Odin3 v3.07.exe



3) Click 'Bootloader' button and load "SM-T310_Boot_Recovery.tar"




- 4) Enter download mode with the normal phone(SD Card inserted).
※ Download Mode : Volume Down Key + Power Key and press Volume Up key.




<Volume Down key + Power Key>

Volume Up
→



<Download Mode>


5) Connect the phone to PC, using USB cable.



6) Click Start button to copy bootloader to the phone.


Boot Recovery (6/10)

- 7) Disconnect the phone from PC.
- 8) Close the Odin3 v3.07.exe and Run it again.
- 9) Click 'Bootloader' button and load "SM-T310_Boot_Recovery.tar"
And check 'T Flash' option in the Odin, to copy bootloader to SD Card




Boot Recovery (7/10)


- 10) Enter download mode with the normal phone (bootloader was copied before), and connect it to PC again
- 11) Click Start button to copy bootloader to the SD Card




- 12) After downloading, turn off the SM-T310 and remove the SD Card.
→ This SD card will be used to recover boot of the phone.
- 13) Disassemble the 'Rear case' from SM-T310, and disconnect battery connector and re-connect battery connector.




14) Insert SD card(bootloader was copied)to the PBA



16) Connect two test-point with tweezers.



- 17) Turn on the SM-T310 while connect two Test-Point.
And remove tweezers after 5 seconds from turning on the SM-T310.
- 18) You can see message on the LCD





- 19) Click Volume Down Key to enter Download Mode
- 20) Download Full S/W including PIT, Bootloader, PDA, CSC

1. Disassembly

1

Disjoint Hook at REAR // Disassemble REAR



1) Be careful not to make scratch and molding damage!

1) Use Band point of disassembly jig

2 Disassemble SCREW



- 1) Disassemble SCREW(12points)
- 2) Detach Battery connector

3 Disassemble FPCB



- 1) Hold up Main PBA from bottom.
- 2) Be careful not to scratch FPCB


4

Disassemble SPK(L),(R), IF PCB



5

Disassemble PBA



- 1) Hold up Main PBA from FRONT.
- 2) Be careful not to scratch FPCB

2. Assembly

1



Assemble PBA



1) Assemble PBA on Front Ass'y

2

Assemble IF PCB/SPK on FRONT.



1) Assemble Earjack PCB and SPK on Front.

3

Assemble connectors



- 1) Be careful not to scratch FPCB
- 2) Assemble Battery

4


Assemble SCREW



- 1) Drive Screws with torque 1.2 ± 0.1 Kgf/cm²


5

Assemble REAR




1) Assemble REAR hook

Electronic Components (1/2)



Electronic Components (2/2)



TSP Connector



LCD TSP Assy

GH96-06467
A


LCD Connector




Home Key FPCB

GH59-13343
A

SMD parts (TOP side)



SMD parts (Bottom side)



HDC600 3708-002222
5M Camera Connector

F600 2901-001625
F602 2901-001732
Filter for 5M Camera

ANT100, ANT101
3712-001473
Antenna Contact (BT, Wifi,
GPS)


U204 1205-004804
Audio Codec

F601 2901-001625
F603, F604 2901-001732
Filter for LCD



Step	Check point	Result value	Defect point
1	Confirm the defect symptom	-	-
2	Check the battery voltage.	Less than 3.4V	Battery
		More than 3.4V	Go to the next step
3	Check the power-key FPCB.	Abnormal(open, tear, etc)	Power-key FPCB
		Normal	Go to the next step
4	Power on the device and check the power-on sound.	Normal	Front Ass'y
		Abnormal	Go to the next step
5	Check the voltage of the following chips (C524, C522, C521, C532, TP_AP_PS_HOLD)	C524>1.0V, C522>1.0V, C521>1.0V, C532>1.0V TP_AP_PS_HOLD > 1.8V	Go to the next step
		If not the correct value	PMIC (U500)
6	Check the frequency of OSC500(C513)	32KHz	Main chip (UCP400)
		If not the correct value	TCXO (OSC500)

Power problem


Step2



Step5





Step3




Check the power-key FPCB

Step6



Step	Check point	Result value	Defect point
1	Confirm the defect symptom	-	-
2	Check the voltage of V_BUS(C304).	C304 = 5V	Go to the next step
		If not the correct value	Connection status of USB FPCB or U300.
3	Check the charging operating of battery.	Abnormal	IF PMIC(U502)
		Normal	-



Charging




Step	Check point	Result value	Defect point
1	Confirm the defect symptom	-	-
2	Check the LCD connector (HDC702)	Broken, dust, corrosion Insert status	AMOLED connector (HDC702)
		Normal	Go to the next step
3	Replace the TFT LCD	Solved	TFT LCD
		Not solved	Go to the next step
4	Connect a LCD and display on with a power supply (power supply voltage : 4.0V)	-	-
5	Check the voltage of C603 = 19V +/- 1V Notice. It should be measured when the display is activated on	If not the correct value	U602
		C603 = 19V +/- 1V	Go to the next step
6	Check the voltage of C605 = 3.3V Notice. It should be measured when the display is activated on	If not the correct value	U600
		C605=3.3V	Go to the next step
7	Check the voltage of C606 = 1.8V Notice. It should be measured when the display is activated on	If not the correct value	PMIC
		C606 = 1.8V	Go to the next step
8	Check the Signal of following chips (F601, F603, F604) Notice. It should be measured when the display is activated on	If not the correct value	F601, F603, F604
		Same signal compared with a good PBA	MAIN CHIP or PBA

Display problem


- Step2
- Step5



- Step5
- Step6





- Step6
- Step7
- Step8



Step	Check point	Result value	Defect point
1	Confirm the defect symptom	-	-
2	Check the TSP connector (HDC700)	Broken, dust, corrosion	TSP connector (HDC700)
		Normal	Go to the next step
3	Check the voltage of C703 Notice. It should be measured when the display is activated on	If not the correct value	PMIC(U500)
		C703 = 3.3V	Go to the next step
4	Check the voltage of following chips (C700,C701,C702) Notice. It should be measured when the display is activated on	If not the correct value	Touch IC(U701)
		C700,C701 = 1.8V C702 = 5.0V	Go to the next step
5	Check the Signal of following chips (R706,R707,R709) Notice. It should be measured when the display is activated on	If not the correct value	R706,R707,R709
		Same signal compared with a good PBA	Go to the next step
6	Replace the TSP	Solved	TSP
		Not solved	Main chip or PBA



TSP problem







5M CAM Problem

Step	Check point	Result value	Defect point
1	Confirm the defect symptom	-	-
2	Check the 5M CAM connector (HDC900)	Broken, dust, corrosion	5M CAM connector (HDC600)
		Normal	Go to the next step
3	Check the voltage of following chips (C601, C602, C621) Notice. It should be measured when the 5M CAM is activated on	If not the correct value	C601, C602, C629, C630
		C601 = 1.2V, C602 = 1.8V, C621 = 2.8V	Go to the next step
4	Check the clock of C600 Notice. It should be measured when the 5M CAM is activated on	C600 = 12Mhz (Same signal compared with a good PBA)	Go to the next step
		If not the correct value	Main chip
5	Check the F600, F602 Notice. It should be measured when the 5M CAM is activated on	Abnormal	F600, F602
		Normal	Go to the next step
6	Replace the 5M CAM	Solved	5M CAM
		Not solved	Main chip or PBA



5M CAM Problem






1.3M CAM Problem

Step	Check point	Result value	Defect point
1	Confirm the defect symptom	-	-
2	Check the 1.3M CAM connector (HDC602)	Broken, dust, corrosion	1.3M CAM connector (HDC602)
		Normal	Go to the next step
3	Check the voltage of following chips (C612, C613, C614) Notice. It should be measured when the 1.3M CAM is activated on	If not the correct value	C612, C613, C614
		C612 = 1.8V, C613 = 1.8V, C614 = 2.8V	Go to the next step
4	Check the clock of C609 Notice. It should be measured when the 1.3M CAM is activated on	C609 = 24Mhz (Same signal compared with a good PBA)	Go to the next step
		If not the correct value	Main chip
5	Check the F605 Notice. It should be measured when the 1.3M CAM is activated on	Abnormal	F902
		Normal	Go to the next step
6	Replace the 1.3M CAM	Solved	1.3M CAM
		Not solved	Main chip or PBA



1.3M CAM Problem





Step	Check point	Result value	Defect point
1	Confirm the defect symptom	-	-
2	Make a factory reset (*2767*3855#)	Solved	Setting error
		Not solved	Go to the next step
3	Check the speaker connector (Left: HDC200, Right: HDC201)	Broken, dust, corrosion	Speaker connector
		Normal	Go to the next step
4	Replace the speaker module (Left: GH96-06317A, Right:GH96-06319A)	Solved	speaker
		Not solved	Go to the next step
5	Connect a LCD, and power on with a power supply (power supply voltage : 3.8V)	-	-
6	Activate the speaker path (*#0*# → Speaker)	-	-
7	Check the signal of speaker contact (HDC200, HDC201) Notice. It should be measured when the speaker path is activated on	Same signal compared with a good PBA	Speaker Connector (HDC200, HDC201)
		Normal Voltage and No signal	Audio Codec (U204)




Speaker problem

Step3

Step4



Step7




Earphone problem

Step	Check point	Result value	Defect point
1	Confirm the defect symptom (*#0*# → Receiver)	-	-
2	Make a factory reset (*2767*3855#)	Solved	Setting error
		Not solved	Go to the next step
3	Check the Earphone connector(HDC202)	Broken, dust, corrosion	connector
		Normal	Go to the next step
4	Replace the Earjack module (GH59-13405A)	Solved	Earjack
		Not solved	Go to the next step
5	Connect a LCD, and power on with a power supply (power supply voltage : 3.8V)	-	-
6	Activate the Speaker path (*#0*# → Speaker(L), Speaker(R))	-	-
7	Check the signal of D204, D207 Notice. It should be measured when the Earphone path is activated on	Same signal compared with a good PBA	Earphone
		No signal	Audio codec (U204)




Earphone problem



Step3



Step4



Step7





Microphone problem

Step	Check point	Result value	Defect point
1	Confirm the defect symptom	-	-
2	Check the microphone hole	Dust	Clean the hole
		Normal	Go to the next step
3	Check the microphone rubber	Wrong insert	Re-insert
		Normal	Go to the next step
4	Activate the speaker path (*#0283# → Packet Loopback ON)	-	-
5	Check the MIC connector (HDC701)	Broken, dust, corrosion	MIC connector
		Normal	Go to the next step
6	Check the signal of TP_704 Notice. It should be measured when the microphone path is activated on	Same signal compared with a good PBA	Microphone
		If not the correct value	AUDIO CODEC(U204)
7	Check the signal of C204, C215 Notice. It should be measured when the microphone path is activated on	Same signal compared with a good PBA	Microphone
		If not the correct value	AUDIO CODEC(U204)




Microphone problem


Step2,3





Step5



Step6



Step7




Step	Check point	Result value	Defect point
1	Confirm the defect symptom (Check the turned on BT/WIFI & connected device)	Turned on	Go to the next step
		Turned off	Turn on
2	Check the BT/WIFI Ant. & Ant contact. (Ant. & ANT100,ANT101)	Broken, dust, corrosion	Ant & ANT100, ANT101
		Normal	Go to the next step
3	Check the voltage of C135 Notice. It should be measured when the BT/WIFI path is activated on	C135 = 1.8V	Go to the next step
		If not the correct value	PMIC (U500)
4	Check the clock of R120, C150, C151 Notice. It should be measured when the BT/WIFI path is activated on	R120 = 37Mhz (Same signal compared with a good PBA)	BT/WIFI IC (U104)
		If not the correct value	OSC101

BT/WIFI Problem

Step1



Step2





ANT101,ANT101



BT/ WIFI ANTENNA
(Carrier TYPE)


Step3,4




Step	Check point	Result value	Defect point
1	Confirm the defect symptom (Check the turned on GPS function)	Turned on	Go to the next step
		Turned off	Turn on
2	Check the BT/WIFI Ant. & Ant contact. (Ant. & ANT100, ANT101)	Broken, dust, corrosion	BT/WIFI Ant & ANT100, ANT101
		Normal	Go to the next step
3	Check the voltage of C110, C113, L101 Notice. It should be measured when the GPS path is activated on	C110 = 1.8V C113, L101 = 2.8V	Go to the next step
		If not the correct value	PMIC(U500)
4	Check the clock of OSC100 Notice. It should be measured when the GPS path is activated on	OSC100 = 26Mhz (Same signal compared with a good PBA)	GPS IC(U102) GPS LNA(U101)
		If not the correct value	OSC100

GPS/GLONASS Problem

Step1





Step2



You can check the this layout if open the shield cover

Step3,4



- Question

